

Port Forwarding on Verizon Router

Actiontec GT704WG & GT704WGB gateways

Step 1: Open your web browser and enter the router IP address ("192.168.1.1" by default) in the address bar. Enter username ("admin" by default) and then password ("password" by default)



Step 2: Click **Security** > **Applications**. Select the camera on your network where you want to use port forwarding in the **PC Name** field. Select **User** in the **Category** list and click **New**.

felloutac	Setup Setup Setup Network Control					
me	Applications					
scurity	When running or accessing certain Internet Applications from your home network, a required port or range of ports specific to the application will need to be opened through the Gateway's firewall. Follow the steps below to open the appropriate ports through the firewall.					
dmin User ame & assword						
rewall						
ettings	Step 1. If not already listed, select the PC that will utilize the application.					
Applications	Step 2. Choose the collected configuration under the Orthogon contine balance A default list of					
MZ Hosting	Step 2. Choose the selected application under the Category section below. A default list of available rules specific to that category will be generated.					
TAT	Step 3. In the Available Rules box, select the rule that applies to your application then click					
	Step 3. In the Available Rules box, select the rule that applies to your application then click					
	Step 3. In the Available Rules box, select the rule that applies to your application then click Add.(To view the rule settings, highlight the desired rule and click the View Rule button).					
	Step 3. In the Available Rules box, select the rule that applies to your application then click Add.(To view the rule settings, highlight the desired rule and click the View Rule button). Step 4. Click the Apply button for the settings to take affect.					
	 Step 3. In the Available Rules box, select the rule that applies to your application then click Add. (To view the rule settings, highlight the desired rule and click the View Rule button). Step 4. Click the Apply button for the settings to take affect. Note: If the category and available rule is not listed for your application, you can create a rule by choosing the User option under the Category section. This will generate the New. Edit and Delete buttons. Click the New button to create the nile. Once the rule has been created, the ability to Edit or Delete the rule is available by clicking on the appropriate button. 					
	Step 3. In the Available Rules box, select the rule that applies to your application then click Add. (To view the rule settings, highlight the desired rule and click the View Rule button). Step 4. Click the Apply button for the settings to take affect. Note: If the category and available rule is not listed for your application, you can create a rule by choosing the User option under the Category section. This will generate the New. Edit and Delete buttons. Click the New button to create the nule. Once the rule has been created, the ability to Edit or Delete the nule is available by clicking on the appropriate button. PC Name: Categora					
	Step 3. In the Available Rules box, select the rule that applies to your application then click Add. (To view the rule settings, highlight the desired rule and click the View Rule button). Step 4. Click the Apply button for the settings to take affect. Note: If the category and available rule is not listed for your application, you can create a rule by choosing the User option under the Category section. This will generate the New. Edit and Delete buttons. Click the New button to create the nile. Once the rule has been created, the ability to Edit or Delete the rule is available by clicking on the appropriate button. PC Name: Category Available Rules Applied Rules					
	Step 3. In the Available Rules box, select the rule that applies to your application then click Add. (To view the rule settings, highlight the desired rule and click the View Rule button). Step 4. Click the Apply button for the settings to take affect. Note: If the category and available rule is not listed for your application, you can create a rule by choosing the Weer cotion under the Category settion. This will generate the New. Edit and Delete buttons. Click the New button to create the nile. Once the rule has been created, the ability to Edit or Delete the rule is available by clicking on the appropriate button. Category Available Rules Applied Rules O games Example Doom					
	Step 3. In the Available Rules box, select the rule that applies to your application then click Add. (To view the rule settings, highlight the desired rule and click the View Rule button). Step 4. Click the Apply button for the settings to take affect. Note: If the category and available rule is not listed for your application, you can create a rule by choosing the Weer sotion under the Category settion. This will generate the New. Edit and Delete buttons. Click the New button to create the nile. Once the rule has been created, the ability to Edit or Delete the rule is available by clicking on the appropriate button. Category Available Rules Applied Rules O Games Example Doom					
	Step 3. In the Available Rules box, select the rule that applies to your application then click Add. (To view the rule settings, highlight the desired rule and click the View Rule button). Step 4. Click the Apply button for the settings to take affect. Note: If the category and available rule is not listed for your application, you can create a rule by choosing the User sotion under the Category settion. This will generate the New, Edit and Delete buttons. Click the New button to create the nule. Once the rule has been created, the ability to Edit or Delete the rule is available by clicking on the appropriate buttons. Category Available Rules Applied Rules VPN Audio/Video Add>>					
	Step 3. In the Available Rules box, select the rule that applies to your application then click Add. (To view the rule settings, highlight the desired rule and click the View Rule button). Step 4. Click the Apply button for the settings to take affect. Note: If the category and available rule is not listed for your application, you can create a rule by choosing the User sotion under the Category settion. This will generate the New, Edit and Delete buttons. Click the New button to create the rule. Once the rule has been created, the ability to Edit or Delete the rule is available by clicking on the appropriate buttons. VEN Available Rules Applied Rules VPN Audio/Video Add>> Apps Remove Category					

www.foscam.com

Step 3: Enter a name for your port forwarding rule in the **Rule Name** field. Select TCP in protocol and enter camera's port number in port start, port end and port map start. Click **Apply** to save your rule settings.

Actiontec®	1	۷ 🖲	3	2	s 🔶	
CHOINTEC	Status Q	uick Wireless etup Setup	Advanced Setup	My Secu	rity Parental Control	Utilities
Home Ru	le Manageme	nt				
Security	Dula N	ame Compret				
Admin User Name &	Prot					
Firewall Settings	Port S	Start 8090	'	Port End 8090		
Applications	Port nap :	E 8090				
DMZ Hosting			Apply			
NAT	Protocol	Port Start	Port End Back	Port Map	Delete	
Actiontec®	Status S	Quick Wireless Setup	Advanced Setup	My Network See	curity Parenta Control	Utilities
Home Ru	le Manageme	ent				
Security	Dula	1ama 1				
Admin User Name & Password	Pro	tocol TCP	•			
Firewall Settings	Port Port Map	Start		Port End		
Applications			Apoly			
DMZ Hosting			and the second s			
NAT						
	Protocol	Port Start	Port End	Port Mag	Delete	1
	TCP	8090	8090	8090		J
			Back			

Click **Back** to return to the Applications screen.

Step 4: Select the name of the rule you just created in the **Available Rules** box and click **Add** to use this port forwarding rule on camera. Click **Apply**.

Category		Applied Rules
) Games		Could be a could be could be could be a could be a could be a could be a coul
O VPN		
Audio/Video	Add	d>>
Apps		
) Servers	Ken	love
User		
N	ew Edit Delete	

www.foscam.com

FOSCAM

You can check port is forwarded successful or not from http://www.yougetsignal.com/tools/open-ports/ .

you get signal	T3/CT3 Compatible Inter	L Port T3/CT3 Compatible Interface Module In Stock.Same Day Shipping. www.ICTCompany.com AdChoices ▷		
Port Forwardi your external add 14.153.222.148 open port finder Remote Address 14.153.222	ng Tester ress 2.148 Port Number 8090 Che	Common ports 21 FTP 22 SSH 23 TELNET 25 SMTP 53 DNS 80 HTTP 110 POP3 115 SFTP 135 RPC 139 NetBIOS 143 IMAP 194 IRC		
Port 8090 is open on 14.1	153.222.148.	443 SSL 445 SMB 1433 MSSQI		

Step 5: View camera over Internet by external IP address or host name and port number.

(Eg: http://14.153.222.148:8090 or http://tech3.dyndns-remote.com:8090)

← < />	53.222.148:8090 🔎 🗕 🗟 🖒 🗙	🖉 Device(Foscam Demo1)	× Router
👍 🕘 httpwww.drivehq.d	com- D Absolutely Free Dynar	nic 👌 Google 🗿 ShenZhe	n Foscam Intellig
	Real-time IP Car	nera Monitoring	System
E	nglish Spanish Deutsch Frend	ch Italian Polski 简体中了	Հ 繁体中文
	ActiveX Mode User Password Login	e (For IE Browser)	
) () (e http://tech3	dyndns-remote.com:809	0/ P + 🖻 C X 🥝 S	henZhen Foscam Intelligent T 🥞 TL-F
httpwww.drivehq.o	com- 🖸 Absolutely Free	Dynamic 猪 Google	🗿 ShenZhen Foscam Intellig
	Rea English	I-time IP Can Spanish Deutsch Frenc	nera Monitoring Syst h Italian Polski 简体中文 繁体
		ActiveX Mode (For User Password Login	IE Browser)

www.foscam.com